

MARTIN WISMAN TPU 3250 - 100V pojačalo

Šifra: 8132
 Kategorija proizvoda: 100V pojačala
 Proizvođač: Martin Wisman

Cena: 369,00 EUR



TPU 3250
Amplifier
Features

3 Mic and 3 Aux inputs
 70 V, 100 V PA-outputs
 1 Mic-connection on the front panel, Chime button
 Treble and bass control
 Master-control
 Protection-circuits: over current,
 Screw terminals of 6 zone outputs

1 Line-output
 4-16 Ohms output for connecting a passive speaker-system monitor
 Build in Mp3 player with songs name display
 7-fold level indicator
 19"-dimensions
 short circuit, turn-on delay

Specifications

MODEL	TPU-3060	TPU-3120	TPU-3180 Z6	TPU-3250
Power supply	AC110V~ 60 Hz	AC110V~ 60 Hz	AC110V~ 60 Hz	AC110V~ 60 Hz
Output power	60W RMS	120W RMS	180 W RMS	250 W RMS
Output type	70 V, 100 V or 4-16	70 V, 100 V or 4-16	70 V, 100 V or 4-16	70 V, 100 V or 4-16
Output current at 70V	0.9A	1.4A	2.5 A	3.6 A
Output current at 100 V	0.6A	1.0A	1.8 A	2.5 A
Mic input	5 mV, 600 Ohms	5 mV, 600 Ohms	5 mV, 600 Ohms	5 mV, 600 Ohms
Line input	300 mV, 10 kOhms	300 mV, 10 kOhms	300 mV, 10 kOhms	300 mV, 10 kOhms
Frequency range	80 Hz - 16 kHz	80 Hz - 16 kHz	80 Hz - 16 kHz	80 Hz - 16 kHz
Distortion	0.5 % (1 kHz)	0.5 % (1 kHz)	0.5 % (1 kHz)	0.5 % (1 kHz) 0.5
Signal/Noise ratio:	Aux	85 dB	85 dB	85 dB
	Mic	75 dB	75 dB	75 dB
FUSE	T2A/250V	T2A/250V	T2A/250V	T5A/250V
Carton dimensions	535X375X175mm	550X425X180mm	550X425X180mm	550X455X180mm
Weight	9.25kg	11kg	12 kg	14 kg